

MURATEC FAX METER READINGS

Model	Instruction
95	Press Enter, Enter, Enter, Press Arrow to tight until ser mode 4, " Enter", "Arrow until prints, Stop Twice to get to ready
100	Press Program Press * Press 9 Enter and the letter C on the one touch keys Screen should say life monitor with a number under it. This is the meter
120	Press Program Press * Press 9 Enter and the letter C on the one touch keys Screen should say life monitor with a number under it. This is the meter
1500	Press Program Press * Press 9 Enter and the letter C on the one touch keys Screen should say life monitor with a number under it. This is the meter
1600	Press P, Press *, Press 9, Press Enter, Lift up flap on the left side and press the one touch key that says E.
2000	Press Program Press * Press 9 Press down until you see page printed
2500	Press menu button, Press Machine Setting on bottom of the screen, select A, Press enter, Screen will show total print pages
F100	Press program * 9, Press enter, Press C it will display your meter count
F120	Press program * 9, Press enter, Press C it will display your meter count
F120	Press program * 9, Press enter, Press C it will display your meter count
F1430	Press "setting" and then "counter," meter is "pages printed".
F150	Press program * 9, Press enter, Press C it will display your meter count
F1500	Put the machine into the "FAX" mode, then press Program,*, 9 (the display will show "Life monitor"), then press ENTER. Press the one touch letter "C" (must be the capital letter C). The total pages printed will be displayed. You can then press the STOP key to exit the test mode.
F1600	Press P, Press *, Press 9, Press Enter, Lift up flap on the left side and press the one touch key that says E.
F160	Press program * 9, Press enter, Press C it will display your meter count
F2000	Press program * 9, Press enter, Press C it will display your meter count
F300	Menu 2,1,1,1 to get meter
F320	Press Menu, Press *, Press 09, Press Enter, Press14, Pages Printed is the meter.
F360	Press Menu, *, 0,9, Enter. The display will show "LIFE MONITOR". It will also display various counts. Press the down arrow key until the pages printed shows in the display. That is the meter.

F520	Press "setting" and then "counter," meter is "pages printed".
F560	Press "setting" and then "counter," meter is "pages printed".
F60	HAS NO METER
F95	Press program * 9, Press enter, Press C it will display your meter count
F98	Press program * 9, Press enter, Press C it will display your meter count
F110	Press key that says "report help", left arrow, then start. Will print system data list page containing meter/counter.
F1300	Press P, *, 9, (screen will read Life Monitor), press enter, lift flap on left hand side and press E
MFX1200	Press PROGRAM key, *, 9, ENTER, then press the One-touch D - P to select the desired display. Press Stop exit.
MFX1430	Press "setting" and then "counter," meter is "pages printed".
MFX1500	Put the machine into the "FAX" mode, then press Program, *, 9 (the display will show "Life monitor"), then press ENTER. Press the one touch letter "C" (must be the capital letter C). The total pages printed will be displayed. You can then press the STOP key to exit the test
MFX1600	Press 'P', *, 9, enter. Lift flap on left side that says 'Copy/Fax' and press the letter 'E', and it will display the meter.
MFX1700	Press 'P', *, 9, enter. Lift flap on left side that says 'Copy/Fax' and press the letter 'E', and it will display the meter.
MFX2000	Press program * 9, Press enter, Press C it will display your meter count
MFX2030	Press "setting" and then "counter," meter is "pages printed".
MFX2530	Press MENU, *, 9. Select "A. Life Monitor", then press [Enter]. The software version, and the counts will be displayed, press [Reset] to exit and return to the standby mode.